

Air Cooler Motors

Motor Structure	Type		Number of phases	Frequency	Voltage	Output Power		Speed		Current		Ins. Cl.	IP	Rotation
	Com. Code	Mfg. Code				Low	High	Low	High	Low	High			
						Hz.	V	W	W	R.P.M	R.P.M			
Permanent Split Phase (Capacitor Run)	CL120	16120	1	50	220/230	145	373	940	1435	1.6	3.7	B	22	C.W
	CL130	16130	1	50	220/230	1.9 HP	1.3 HP	950	1425	1	2.4	B	22	C.W
	CL132	16132	1	50	220/230	100	249	940	1425	1	2.8	B	22	C.W
	CL140	16140	1	50	220/230	1.12 HP	1.4 HP	950	1400	0.9	1.6	B	22	C.W
	CL142	16142	1	50	220/230	80	187	940	1400	1	1.9	B	22	C.W
	CL141	16180	1	50	220/230	180		1350		2.5		B	22	C.W
	CL340	16340	1	50	220/230	1.4 HP	3.4 HP	950	1425	1.7	4.3	B	22	C.W