

Air Cooler Motors

Motor Structure	Type		Number of phases	Frequency	Voltage	Output Power		Speed		Current		Ins. Cl.	IP	Rotation
	Com. Code	Mfg. Code				Low	High	Low	High	Low	High			
						Hz.	V	W	W	R.P.M	R.P.M			
Split Phase		18340	1	50	220	165	560	960	1425	3.2	6.2	B	22	C.W
	EM120	28120	1	50/60	220	1.6 HP	1.2 HP	950	1425	2.7	5.8	B	22	C.W
								1140	1725	2.3	4.7			
	EM130	28130	1	50/60	220	1.10 HP	1.3 HP	950	1425	2.1	4	B	22	C.W
								1140	1725	1.8	3.3			
	EM340	29340	1	50/60	220	1.4 HP	3.4 HP	950	1425	3.2	6	B	22	C.W
								1140	1725	2.8	5.5			